

# Meridian Compact Programming

## A. Configuration

### 1. Line Data (Show line: )

External handling

(Exchange lines 01 to 06)

Recall: **Timed brk**, Earth 500, Earth 1000, Earth 1500

Dial mode: Pulse, **Tone**

Recall at EXCH: **N**

Full AutoHold: **N**

(AC15A private circuits 07 to 08)

Ans Mode: **Manual**, Auto

Amplified AC15: **Y**

Gain: **Compatible**, Other

(if Gain: Other) Transmit vol: 1, 2, 3, 4, 5, 6, 7

(if Gain: Other) Receive vol: 1, 2, 3, 4, 5, 6, 7

Dial mode: Pulse, **Tone**

Recall at EXCH: **N**

Full AutoHold: **N**

(Direct Inward Access lines 11 to 26)

Rec'd #: **None** (1 to 7 digits)

Internal handling

Line type

Line 01: **Pool A**, Public, Private to:, Pool:

Line 02-06: **Public**, Private to:, Pool:

Line 07-08: **Pool C**, Public, Private to:, Pool:

Line 11 to 26: **Public**, Private to:

Prime extn: **21**, (other available extensions)

Aux. ringer: **Y**

### 2. Line Access (Show extn#: )

Line assignment (Show line: )

Extension 21

Line 01: **Appear&Ring**, Appear only, Not assignd,

Ring only

Line 02: **Appear&Ring**, Appear only, Not assignd,

Ring only

Line 03: **Appear&Ring**, Appear only, Not assignd,

Ring only

Line 04: **Appear&Ring**, Appear only, Not assignd,

Ring only

Lines 05 to 26: Appear&Ring, Appear only, **Not**

**assignd**, Ring only

Other extensions

Lines 01 to 04: Appear&Ring, **Appear only**, Not

assignd, Ring only

Lines 05 to 26: Appear&Ring, Appear only, **Not**

**assignd**, Ring only

Line pool access:

Pool A: **Y**, Pool B: **N**, Pool C: **Y**

Intercom keys: 0,1, 2

Prime line: **I/C**, Pool A to C, line 01 to 06, none

### 3. Routing Table (DestCode: )

DestCode: (max 7 digits)

Use: Pool A, Pool B, **Pool C**

DialOut: (max 24 digits)

### 4. Call Handling

Held reminder: **Y**

Remind delay: 30, **60**, 90, 120, 150, 180

DRT to prime: **Y**

DRT delay: 1,2,3,4,6

Netwlc callbk: 15, **30**, 45, 60, 90

Trnsfr callbk: 3, 4, 5, 6, 12

Park timeout: 30, 45, **60**, 90, 120, 150, 180, 300, 600

Confrence tone: **Y**

On hold: **Tones**, Music, Silence

### 5. Miscellaneous

Backgrnd music: **N**

Auto#: **None**

Extn Relocatn: **N**

Host delay: 1000,1500,2000,2500,3000,**3500** 4000,  
4500, 5000, 5500, 6000, 6500, 7000

EXCH ring: **Preset**, Echo

PCct delay: 200,**800**,1600

Exchange code: 0, 1, 2, 3, 4, 5, 6, 7, 8, **9**

Line pool codes

A: **9**, B: **blank** C: **blank**

Installer pswd: **CONFIG**

### 6. System Data

Individual exfns

Extn # length: 2, 3, 4, 5, 6, 7

Rec'd # length: 1,2, 3, 4, 5, 6, 7

## B. General Admin

### 1. Sys speed dial

Speed dial #:

01 - 70: **No number stored**

Line: **Use prime line**, Use line: \_\_\_, Pool code: \_\_\_,

Use routing tab!

Display digits: **Y**

(if Display digits set to N) Name :

01 to 70: **Sys Spd Dial 01**, (as assigned, up

to 16

characters) Bypass restr'n: **N**

### 2. Names

Extn names (Show extn#: )

21: **21** etc.

Line names (Show line: )

Line 01: **Line 01** etc.

### 3. Time and Date

Time: (present system time)

Date: (present system date)

### 4. Direct-Dial

D-Dial 1: **Intnl**, Extrnl, None

(ifIntnl):21

(if Extrnl:) Extrnl #: **None**

(if Extrnl:) **Use prime line**, Use line:.

Use routing tab!

### 5. Restrictions

Table entries

01:0

02:1

03:010

04:00

05 to 30: (blank)

Applied to lines (Show line: )

Line 01 to 08: (as assigned)

Applied to extensions (Show extn#: )

### 6. Overrides

Table entries

01 to 10: (blank)

Applied to lines (Show line: )

Line 01 to 08: (as assigned)

Applied to extensions (Show extn#: )

### 7. Permissions (Show extn#: )

ExtnLock: **None**, Full, Partial

Full handsfree: **N**

(if Full handsfree: Y) Auto handsfree: **N**

HF answerback: **Y**

Pickup group: **NO**, 1, 2, 3, 4

Page zone: **NO**, 1, 2, 3

Aux. ringer: **N**

Forward on busy:

Forward to: **None**

Forward no answer :

Forward to: **None**

Forward delay 2,3,4,6, 10

DND on busy **N**

Receive tones: **N**

Redirect ring: **Y**

Hotline: **None**, Intrnl, Extrnl

(if Extrnl: **Use prime line**, Use line: \_\_\_, Pool code

use routing tab!)

Priority call: **N**

ATA settings

ATA mode: Pulse, **Tone**

ATA tones: **N**

### 8. Service modes

Control extns (Show line: )

All lines: **21**

Name 1: **Night**, (max 7 chars)

Setting: **Manual**, Off

Trunk answer: **Y**

Extra-0 extn

Show line: \_

Ringing extns: (Show line: )

(all lines): Extn: **21**

Aux. ringer: **Y**

Name 2: **Evening**, (max 7 chars)

Setting: **Manual**, Off

Trunk answer: **Y**

Extra-0 extn

Show line: \_

Ringing extns: (Show line: )

(all lines): Extn: **21**

Aux. ringer: **Y**

Name 3: **Lunch**, (max 7 chars)

Setting: **Manual**, Off

Trunk answer: **Y**

Extra-0 extn

Show line: \_

Ringing extns: (Show line: )

(all lines): Extn: **21**

Aux. ringer: **Y**

### 9. Passwords

Admin password: **ADMIN**, (as assigned)

Restriction pswd (Show pswd: )

00 to 24: **blank** (as assigned, 4 digits)

### 10. Clear Lines (no settings)

## C. Extension Copy

Copy **SYSTEM data**, SYSTEM + USER

## D. System version